

ACTIONS

CONDITION	REQUIRED ACTION	COMPLETION TIME
A. One required offsite circuit inoperable.	A.1 Perform SR 3.8.1.1 for required OPERABLE offsite circuit.	1 hour <u>AND</u> Once per 8 hours thereafter
	<u>AND</u> -----NOTE----- In MODES 1, 2 and 3, the TDAFW pump is considered a required redundant feature. -----	
	A.2 Declare required feature(s) with no offsite power available inoperable when its redundant required feature(s) is inoperable.	24 hours from discovery of no offsite power to one train concurrent with inoperability of redundant required feature(s)
	<u>AND</u>	
	A.3 Restore required offsite circuit to OPERABLE status.	72 hours <u>AND</u> 6 days from discovery of failure to meet LCO <u>OR</u> 21 days for a one time preventive maintenance outage on Startup Transformer XST2 to be completed by February 28, 2002

(continued)