

3.8 ELECTRICAL POWER SYSTEMS

3.8.1 AC Sources—Operating

LCO 3.8.1 The following AC electrical power sources shall be OPERABLE:

- a. Two qualified circuits between the offsite transmission network and the onsite Class 1E AC Electric Power Distribution System; and
- b. Three diesel generators (DGs).

APPLICABILITY: MODES 1, 2, and 3.

-----NOTE-----
Division 3 AC electrical power sources are not required to be OPERABLE when High Pressure Core Spray System is inoperable.

ACTIONS

CONDITION	REQUIRED ACTION	COMPLETION TIME
A. One offsite circuit inoperable.	A.1 Perform SR 3.8.1.1 for OPERABLE offsite circuit.	1 hour <u>AND</u> Once per 8 hours thereafter
	<u>AND</u> A.2 Restore offsite circuit to OPERABLE status.	72 hours <u>AND</u> 17 days from discovery of failure to meet LCO

(continued)

ACTIONS (continued)

CONDITION	REQUIRED ACTION	COMPLETION TIME
B. One required DG inoperable.	B.1 Perform SR 3.8.1.1 for OPERABLE offsite circuit(s).	1 hour <u>AND</u> Once per 8 hours thereafter
	<u>AND</u>	
	B.2 Declare required feature(s), supported by the inoperable DG, inoperable when the redundant required feature(s) are inoperable.	4 hours from discovery of Condition B concurrent with inoperability of redundant required feature(s)
	<u>AND</u>	
	B.3.1 Determine OPERABLE DG(s) are not inoperable due to common cause failure.	24 hours
	<u>OR</u>	
	B.3.2 Perform SR 3.8.1.2 for OPERABLE DG(s).	24 hours
	<u>AND</u>	
	B.4 Restore required DG to OPERABLE status.	72 hours from discovery of an inoperable Division 3 DG <u>AND</u> 14 days <u>AND</u> 17 days from discovery of failure to meet LCO

(continued)