

ACTIONS

CONDITION	REQUIRED ACTION	COMPLETION TIME
A. One required offsite circuit inoperable.	A.1 Perform SR 3.8.1.1 for OPERABLE required offsite circuit.	1 hour <u>AND</u> Once per 8 hours thereafter
	<u>AND</u> A.2 Declare required feature(s) with no offsite power available inoperable when the redundant required feature(s) are inoperable.	24 hours from discovery of no offsite power to one division concurrent with inoperability of redundant required feature(s)
	<u>AND</u> A.3 Restore required offsite circuit to OPERABLE status.	72 hours <u>AND</u> 17 days from discovery of failure to meet LCO 3.8.1.a or b

(continued)

ACTIONS

CONDITION	REQUIRED ACTION	COMPLETION TIME
B. One required Division 1, or 2 DG inoperable. <u>OR</u> Required opposite unit Division 2 DG inoperable.	B.1 Perform SR 3.8.1.1 for OPERABLE required offsite circuit(s).	1 hour <u>AND</u> Once per 8 hours thereafter
	<u>AND</u>	
	B.2 Declare required feature(s), supported by the inoperable DG(s), inoperable when the redundant required feature(s) are inoperable.	4 hours from discovery of Condition B concurrent with inoperability of redundant required feature(s)
	<u>AND</u>	
	B.3.1 Determine OPERABLE DG(s) are not inoperable due to common cause failure.	24 hours
	<u>OR</u>	
	B.3.2 Perform SR 3.8.1.2 for OPERABLE DG(s).	24 hours
	<u>AND</u>	
	B.4 Restore required DG(s) to OPERABLE status.	14 days <u>AND</u> 17 days from discovery of failure to meet LCO 3.8.1.a or b

(continued)

ACTIONS

CONDITION	REQUIRED ACTION	COMPLETION TIME
<p>C. Required Division 3 DG inoperable.</p> <p><u>OR</u></p> <p>One required Division 1, 2, or 3 DG inoperable and the required opposite unit Division 2 DG inoperable.</p>	C.1 Perform SR 3.8.1.1 for OPERABLE required offsite circuit(s).	1 hour <u>AND</u> Once per 8 hours thereafter
	<u>AND</u>	
	C.2 Declare required feature(s), supported by the inoperable DG(s), inoperable when the redundant required feature(s) are inoperable.	4 hours from discovery of Condition C concurrent with inoperability of redundant required feature(s)
	<u>AND</u>	
	C.3.1 Determine OPERABLE DG(s) are not inoperable due to common cause failure.	24 hours
	<u>OR</u>	
	C.3.2 Perform SR 3.8.1.2 for OPERABLE DG(s).	24 hours
	<u>AND</u>	
	C.4 Restore required DG(s) to OPERABLE status.	72 hours <u>AND</u> 17 days from discovery of failure to meet LCO 3.8.1.a or b

(continued)

ACTIONS

CONDITION	REQUIRED ACTION	COMPLETION TIME
<p>F. Two required Division 1, 2, or 3 DGs inoperable.</p> <p><u>OR</u></p> <p>Division 2 DG and the required opposite unit Division 2 DG inoperable.</p>	<p>F.1 Restore one required DG to OPERABLE status.</p>	<p>2 hours</p> <p><u>OR</u></p> <p>72 hours if Division 3 DG is inoperable</p>
<p>G. Required Action and associated Completion Time of Condition A, B, C, D, E, or F not met.</p>	<p>G.1 Be in MODE 3.</p> <p><u>AND</u></p> <p>G.2 Be in MODE 4.</p>	<p>12 hours</p> <p>36 hours</p>
<p>H. Three or more required AC sources inoperable.</p>	<p>H.1 Enter LCO 3.0.3.</p>	<p>Immediately</p>