

Davis Besse Power Station
Transmittal / Receipt Acknowledgement

Control Copy Number: 1665

Transmittal Number: 0305-29622

Transmittal Date: 05-30-2003

To: DOC. CONTROL DESK

Mail Stop / Address: USNRC DIVISION OF EMERGENCY PREPARDNESS WASHINGTON, D.C. 20555

Document holders are responsible for control and maintenance of documents in accordance with the actions specified by this transmittal. Outdated material shall either be removed and destroyed or marked to reflect that it is superseded or voided and is no longer considered controlled.

Note: Destroy Safeguard information by shredding.

File documents in tab order as identified on the Table of Contents Contact Document Control with any questions at (419)-321-7483

7015

Davis Besse Power Station
Transmittal / Receipt Acknowledgement

Control Copy Number: 1665

Transmittal Number: 0305-29622

Transmittal Date: 05-30-2003

		Document						
TOC 1	TOC 2	Type	Number	Sht/Sec	Changes	Rev	Status	
old	EPOC	EPON	PROC	RA-EP-02810		0002	APPROVED	
new	EPOC	EPON	PROC	RA-EP-02810		0003	APPROVED	

Davis-Besse Nuclear Power Station

EMERGENCY PLAN OFF NORMAL OCCURRENCE PROCEDURE

RA-EP-02810

TORNADO

REVISION 03

Prepared by: B.W. Cope

Procedure Owner: Manager - Security

Effective Date: MAY 30 2003

Procedure Classification:

☒ Safety Related
☐ Quality Related
☐ Non-Quality Related

LEVEL OF USE:

IN-FIELD REFERENCE

TABLE OF CONTENTS

	<u>Page</u>
1.0 PURPOSE	3
2.0 REFERENCES	3
3.0 DEFINITIONS	3
4.0 RESPONSIBILITIES	3
5.0 INITIATING CONDITIONS	4
6.0 PROCEDURE	5
6.1 Activation	5
6.2 Operation During a Tornado Watch	5
6.3 Operation During a Tornado Warning or Report of a Tornado Sighting near the Plant ..	6
7.0 FINAL CONDITIONS	7
8.0 RECORDS	8
COMMITMENTS	9

1.0 PURPOSE

This procedure describes the actions that shall be taken when weather conditions favor the formation of tornadoes.

2.0 REFERENCES**2.1 Developmental**

2.1.1 Davis-Besse Nuclear Power Station Emergency Plan

2.1.2 NUMARC 87-00, Guidelines and Technical Bases for NUMARC Initiative
Addressing Station Blackout at Light Water Reactors

2.2 Implementation

2.2.1 RA-EP-01500, Emergency Classification

2.2.2 DB-OP-02550, Dry Fuel Storage Abnormal Events

3.0 DEFINITIONS

3.1 **TORNADO WATCH** - a forecast issued in advance of a severe weather event to alert the public to conditions which may favor the formation of tornadoes.

3.2 **TORNADO WARNING** - A notice issued as a result of a sighting of a tornado in the warning area, or as determined through the interpretation of Radar Imaging.

4.0 RESPONSIBILITIES

4.1 The Shift Manager shall be responsible for:

4.1.1 Notifying the Supervisor - Security Shift of a tornado watch or warning.

4.1.2 Notifying the On-Call Emergency Offsite Manager of a tornado watch or warning.

4.2 The Supervisor - Security Shift shall:

4.2.1 Advise the Shift Manager of any messages received concerning tornado information.

NOTE 4.2.2

Notification of Owner Controlled Area personnel is dependent upon shift
manning and weather compensatory measures that may be in effect.

4.2.2 Ensure Security notifies individuals in remote areas of the Owner Controlled Area of a tornado warning.

5.0 INITIATING CONDITIONS

This procedure shall be utilized when the Control Room has been made aware of a tornado watch or a tornado warning for areas, which include the power station.

- 5.1 The Shift Manager should instruct Control Room personnel to monitor available weather information for adverse weather trends or notices from the National Weather Service.

6.0 PROCEDURE**6.1 Activation****6.1.1 The Control Room operator shall:**

- a. Inform the Shift Manager of a tornado watch or tornado warning for Ottawa County.
- b. Closely and continuously monitor the Control Room panels to determine any effects on instrumentation, controls, or station operations.

WARNING 6.1.2.

1. Weather conditions may make inspection of outside areas hazardous.
2. Tornado may occur with little or no warning. They may occur prior to the National Weather Service or the Ottawa County issuing the warning.
3. At the discretion of the Shift Manager, actions in Section 6.3 may be taken at any time.

6.1.2 At the discretion of the Shift Manager:

- a. Direct an inspection of the Protected Area and switchyard for potential missiles and reduce missile potentials where practical.
- b. Evaluate ongoing maintenance activities and expedite the restoration of important plant systems and components to service.
- c. Direct that weather conditions be monitored via local television channel or web weather site such as Weather.com or Intellicast.com.

6.2 Operation During a Tornado Watch**6.2.1 In the event of a tornado watch for areas which include the power station, the Shift Manager shall notify:**

- a. The Supervisor - Security Shift
- b. On-Call Emergency Offsite Manager

6.2.2 The Supervisor - Security Shift shall direct security patrols to:

- a. Report any tornado sightings to the Control Room.
- b. Advise the Shift Manager on any messages received concerning tornado information.

NOTE 6.3

All of the applicable actions in Section 6.3 should be taken on receiving a Tornado Warning or report from a credible source of a tornado sighting near the plant. The Shift Manager will determine credibility of the source.

6.3 Operation During a Tornado Warning or Report of a Tornado Sighting near the Plant**6.3.1 The Shift Manager shall ensure:**

- a. Announcement of the tornado warning over the GaiTronics System
 - 1. **IF** containment closure is not set,
THEN announce "Establish Containment Closure".
- b. Notification of the Supervisor – Security Shift of the tornado warning.
- c. Notification of the On-Call Emergency Offsite Manager of the tornado warning.
- d. Notification of the On-Call Plant Manager.

CAUTION 6.3.1.e & f

To minimize the possibility of a complete loss of AC power, **DO NOT** parallel the Emergency Diesel Generators (EDGs) with the C1 or D1 busses.

- e. In Modes 1 through 4:
 - 1. Ensure that both the EDGs are started and set at idle speed.
 - 2. Instruct station personnel to prepare for a rapid shut-down of the plant.
- f. In Modes 5 and 6:
 - 1. Ensure that both EDG's are started and set at idle speed.
 - 2. Order all fuel handling operations suspended.
IF fuel is being supported from a crane or a bridge,
THEN order it placed into a safe storage location.
 - 3. Direct that containment closure be established to the maximum extent practical to include installing the containment Equipment Hatch.
- g. Suspend all movement of radioactive waste until the tornado warning has been canceled.

- h. Order all nonessential station operations halted.
- i. Use RA-EP-01500, Emergency Classification, to determine the proper emergency classification, if any, and take appropriate actions.

CAUTION 6.3.2

Notification of Owner Controlled Area personnel is dependent upon shift manning and weather compensatory measures that may be in effect.

- 6.3.2 The Supervisor - Security Shift shall ensure that Security personnel inform individuals in remote areas of the Owner Controlled Area (OCA) about the tornado warning, as time and conditions permit.

7.0 FINAL CONDITIONS

Use of this procedure shall be terminated when the tornado watch or tornado warning has been canceled.

7.1 The Shift Manager shall ensure:

- 7.1.1 That the EDGs are stopped and restored to normal standby mode.
- 7.1.2 IF an emergency has been declared in accordance with RA-EP-01500, Emergency Classification,
THEN, take actions accordingly.
- 7.1.3 Announcement is made over the Gaitronics system that the tornado threat has expired.
- 7.1.4 REFER TO DB-OP-02550, Dry Fuel Storage Abnormal Events.
- 7.1.5 Notification of the Supervisor - Security Shift that the tornado watch or warning has expired.
- 7.1.6 Notification of the On-Call Emergency Offsite Manager that the tornado watch or warning has expired.
- 7.1.7 Notification of the On-Call Plant Manager that the tornado warning has expired.

8.0 RECORDS

- 8.1** The following quality assurance records are completed by this procedure and shall be listed on the Nuclear Records List, captured, and submitted to Nuclear Records Management in accordance with NG-NA-00106:

8.1.1 None

- 8.2** The following non-quality assurance records are completed by this procedure and may be captured and submitted to Nuclear Records Management, in accordance with NG-NA-00106:

8.2.1 None

COMMITMENTS

<u>Section</u>	<u>Reference</u>	<u>Comments</u>
Entire Procedure	TERMS Q 00070	Acts of Nature Procedure
6.1.2 a & b	PCAQR 93-0531 NUMARC 87-00 Section 4.2.3	PCRs 93-2745, 2323; Implements NUMARC 87-00: Station Blackout
6.3	CA-02-09213-03	Add additional guidance from 11/10/02 lessons learned.
Title Page	CA-01-3101-15	Change level of Use from Step- by-Step to In-Field Reference.
6.3.a.1	CA-02-09213-08	If containment closure is not set, announce "Establish Containment Closure".